

LED Dimmer – DIMMER-WP3

- Professional Installation Recommended
- Supply Voltage DC12-24v
- Max Load 8A
- Never use with AC Power Source
- Test your existing wires with a meter prior to installation to determine source positive and ground wires
- Outer trim cover is removed by pulling straight out. A screwdriver may be used to gently dislodge the cover
- Control Panel is Wireless. A battery is pre-installed and item is shipped with a spare battery.
- Dimmer may be installed with or without the mounting box. Ensure exposed wires and circuitry are not in contact with any items behind dimmer
- Wires are connected to dimmer module. Take note of diagram module for proper incoming and outgoing wiring and polarity.
- Dimming can also be controlled from the module in the event the Control Panel
- If using more than one dimmer, ensure the ID number on each dimmer is unique

