

LED Dimmer – DIMMER-N

- Professional Installation Recommended
- Supply Voltage DC12-24v
- Max Load 8A
- Never use with AC Power Source
- Use in conjunction with existing on/off switch. Red active light will remain on when power is supplied to dimmer
- Test your existing wires with a meter prior to installation to determine source positive and ground wires
- Outer trim cover is removed by pulling straight out. A screwdriver may be used to gently dislodge the cover
- Dimmer may be installed with or without the mounting box. Ensure exposed wires and circuitry are not in contact with any items behind dimmer
- Wires are connected to back of dimmer. Take note of diagram on circuit board for proper incoming and outgoing wiring and polarity.

